

POWERSIL[®] 79032

Silicone Rubber Dispersions

POWERSIL[®] 79032 is an electrically conductive silicone rubber dispersion in Xylene. POWERSIL[®] 79032 can be used as conductive coating and adhesion promoting primer. POWERSIL[®] 79032 comes ready-to-use as a 1-component system.

Properties

- low volume resistivity
- adhesion promoting primer
- ready-to-use
- suitable for various coating techniques like dipping, brushing or spraying

Specific features

- Crosslinking Property: 1-component system
- Specific Features: Electrically conductive
- Vulcanizate: Electrically conductive

Technical data

Properties Uncured

Property	Condition	Value	Method
Solid content	-	25 %	-
Viscosity, dynamic ⁽¹⁾	23 °C	14000 mPa·s	Brookfield
Pot life ⁽²⁾	-	> 30 d	-

¹2.5 rpm

²at 23 °C

These figures are only intended as a guide and should not be used in preparing specifications.

Properties Cured

Cured conditions: 30 min / 150 °C in a circulating air oven.

Property	Condition	Value	Method
Density	23 °C	1.22 g/cm ³	DIN EN ISO 1183-1 A
Volume resistivity	-	5 Ohmcm	IEC 62631-3-1
Appearance	-	black	-
Mix ratio ⁽¹⁾	-	1 : 1	-

¹with Xylene

These figures are only intended as a guide and should not be used in preparing specifications.

All the information provided is in accordance with the present state of our knowledge. Nonetheless, we disclaim any warranty or liability whatsoever and reserve the right, at any time, to effect technical alterations. The information provided, as well as the product's fitness for an intended application, should be checked by the buyer in preliminary trials. Contractual terms and conditions always take precedence. This disclaimer of warranty and liability also applies particularly in foreign countries with respect to third parties' rights.

Applications

- Cable Accessories
- Insulator Coatings

Application details

- cable accessories
- electrodes
- deflectors
- adhesion promoter for moulding RTV-2/LSR onto conductive silicone rubber

Processing

After stirring up POWERSIL® 79032 is ready-to-use. At room temperature the pot life is at least several weeks.

Surfaces to be treated should be dry and free of grease, oil and other contaminants. For cleaning chemically pure solvents e. g. acetone can be used. The dispersion of POWERSIL® 79032 can be applied by dipping, spraying and with a brush.

For electrically conductive coatings we recommend a curing – after air drying for approx. 5 min at room temperature – of at least 30 min at 150 °C.

POWERSIL® 79032 can also be used as adhesion primer for overmoulding parts made from conductive silicone rubber with RTV-2/LSR silicone rubbers.

For adhesion promoting (e. g. for deflectors) POWERSIL® 79032 should be vulcanized – after air drying for approx. 5 min at room temperature – for 20 min at 140 – 150 °C in a circulating air oven. Normally for this application POWERSIL® 79032 is diluted in a 1 : 1 ratio with Xylene. Casting with a RTV-2/LSR silicone rubber should take place at the latest after 24 h. It appeared that the adhesion after heat vulcanization (e. g. 100 °C) mostly is better than after room temperature curing.

By dilution with chemical pure Xylene up to a ratio from 1 : 1 any desired mixing-viscosity (> 500 mPa s) can be adjusted. As a general rule the individual processing conditions must be optimized for the specific application.

Various substances can poison the platinum catalyst and delay vulcanization or, in extreme cases, prevent it entirely. Particularly critical catalyst poisons are: Sulphur, polysulfides, polysulfones and compounds containing sulphur, such as natural and synthetic rubber. Amines, urethanes and substrates containing amines, such as polyurethanes, epoxy resins etc.

Organometallic compounds, especially organo-tin, and substances containing such compounds. Sticky areas are signs of inhibition.

For detailed information, refer to brochures on www.wacker.com.

Packaging and storage

Storage

The 'Best use before end' date of each batch is shown on the product label.

Storage beyond the date specified on the label does not necessarily mean that the product is no longer usable. In this case however, the properties required for the intended use must be checked for quality assurance reasons.

Safety notes

Comprehensive instructions are given in the corresponding Material Safety Data Sheets. They are available on request from WACKER subsidiaries or may be printed via WACKER web site <http://www.wacker.com>.

QR Code POWERSIL® 79032



For technical, quality or product safety questions, please contact:

Wacker Chemie AG, Hanns-Seidel-Platz 4, 81737 Munich, Germany
info@wacker.com, www.wacker.com

The data presented in this medium are in accordance with the present state of our knowledge but do not absolve the user from carefully checking all supplies immediately on receipt. We reserve the right to alter product constants within the scope of technical progress or new developments. The recommendations made in this medium should be checked by preliminary trials because of conditions during processing over which we have no control, especially where other companies' raw materials are also being used. The information provided by us does not absolve the user from the obligation of investigating the possibility of infringement of third parties' rights and, if necessary, clarifying the position. Recommendations for use do not constitute a warranty, either express or implied, of the fitness or suitability of the product for a particular purpose.